


The OLG logo is displayed in white text on a red rectangular background in the top-left corner of the page.


PLANTATION

Assembly Instructions


Plantation

Extendable Rails







STEP 1: Unscrew end rails and remove.



STEP 2: Find the middle point of the center rail and screw the bracket.



STEP 3: Use the center as reference to position both ends back into the center rail symmetrically.



STEP 4: Screw the end rails to the center rail once achieved the desired length.

Plantation

Assembly Instructions – Round Tables 600D





STEP 1: Align the legs at even spacing on the worktop, with the top plate being no closer than 5 mm from the edge of worktop. Mark each leg location for easy fixing in step 2.



STEP 2: Fix the leg to the worktop using 4 x 23 mm self-tapping screws per leg.



STEP 3: Turn the table over.


Plantation

Assembly Instructions – Round Tables 900D





STEP 1: Fix 1x angle brack to each leg using 2 x M12 bolts.



STEP 2: Align the legs at even spacing on the worktop, with the top plate being no closer than 5 mm from the edge of worktop. Mark each leg location for easy fixing in step 3.



STEP 3: Fix the leg to the worktop using 4 x 23 mm self-tapping screws per leg.



STEP 4: Turn the table over.

Plantation

Assembly Instructions – Round Tables 1050D





STEP 1: Fix 1x angle brack to each leg using 2 x M12 bolts.



STEP 2: Align the legs at even spacing on the worktop, with the top plate being no closer than 5 mm from the edge of worktop. Mark each leg location for easy fixing in step 3.



STEP 3: Fix the leg to the worktop using 4 x 23 mm self-tapping screws per leg.



STEP 4: Turn the table over.


Plantation

Assembly Instructions – Round Tables 1200D





STEP 1: Fix 1x angle brack to each leg using 2 x M12 bolts.



STEP 2: Align the legs at even spacing on the worktop, with the top plate being no closer than 5 mm from the edge of worktop. Mark each leg location for easy fixing in step 3.



STEP 3: Fix the leg to the worktop using 4 x 23 mm self-tapping screws per leg.



STEP 4: Turn the table over.

Plantation

Assembly Instructions – Round Tables I500D





STEP 1: Fix 1x rail receiver to each leg using 2 x M12 bolts.
Fix 2x rail receivers to the centre rail using 2 x M12 bolts.



STEP 2: Connect centre rail, 2x short rails, 4 x legs together as shown.



STEP 3: Align frame with worktop and fix down using 4 x 23 mm screws per leg and 4 x 70 mm screws for the rails.



STEP 4: Use 2 persons to turn the table over to be the correct way up.





Plantation

Assembly Instructions - Meeting Table 4 Leg





STEP 1: Assemble 2x end leg frames to the legs. Total 6 x M12 per leg.



STEP 2: Assemble the rail receivers to the crossbar.



STEP 3: Assemble the rails to the end legs and set rail length.



STEP 4: Fix worktop to frame using 4 x 23mm screw per leg, 1 x 23mm screw per rail.


Plantation

Assembly Instructions – Meeting Table 6 Leg






STEP 1: Assemble 2x end leg frames to the legs.
Total 6 x M12 per leg.



STEP 2: Assemble the rail receivers to the crossbar.



STEP 3: Assemble the mid leg using bolts provided in the spreader bar kit. Mount the rail to the centre mounting point.



STEP 4: Assemble the rails to the end legs and set rail length.




STEP 5: Fix worktop to frame using 4 x 23mm screw per leg, 1 x 23mm screw per rail.






Plantation

Assembly Instructions - Desking 2 DSD





STEP 1: Assemble 2x end leg sets as above, including assembling the rail receivers to the crossbar.



STEP 2: Fit rails to end frames and set length to fit worktops.




STEP 3: Align worktops to frame, recommended spacing is 5 mm overhang on the ends and central gap to suit screen type. (S50 = 52 mm, epanel = 20 mm, R18 = 20 mm)




STEP 4: Fix worktop to frame using 4 x 23mm screw per leg, 2 x 23mm screw per rail.


Plantation

Assembly Instructions – 2DSD Studio50 Screen






STEP 1: Fix AXSB bracket to end frame and tighten.



STEP 2: Rest the screen panel on bracket so the end of the screen is equal distance from each end of the setting.




STEP 3: Fix the screen down tightly to the bracket.




Plantation

Assembly Instructions - Desking 4 DSD





STEP 1: Assemble 1x mid leg set including assembling rail receivers to the crossbar.



STEP 2: Fit rails and 5 mm set worktop length to 10 mm less than the overall length.




STEP 3: Align worktops to frame recommended spacing is 5 mm overhang on the ends and central gap to suit screen type. (S50 = 52 mm, epanel = 20 mm, R18 = 20 mm)



STEP 4: Fix worktop to frame using 4 x 23mm screw per leg, 2 x 23mm screw per rail.


Plantation

Assembly Instructions – 4DSD Studio50 Screen




Plantation

Assembly Instructions - 4DSD Studio50 Screen
Same Instructions for 6DSD w/ Studio50 Screen



STEP 1: Fix AXSB bracket to end and mid frame and tighten.



STEP 2: Rest the screen panel on bracket so the end of the screen is equal distance from each end of the setting.





STEP 3: Connect the middle screens and panel finish as per normal studio assembly.




Plantation

Assembly Instructions - Desking 6 DSD





STEP 1: Assemble 1x mid leg set including assembling rail receivers to the crossbar.



STEP 2: Fit rails and 5 mm set worktop length to 10 mm less than the overall length.



STEP 3: Align worktops to frame recommended spacing is 5 mm overhang on the ends and central gap to suit screen type. (S50 = 52 mm, epanel = 20 mm, R18 = 20 mm)



STEP 4: Fix worktop to frame using 4 x 23mm screw per leg, 2 x 23mm screw per rail.


Plantation

Assembly Instructions - Desking Straight Desk





STEP 1: Assemble 2x end leg sets as above, including assembling the rail receivers to the crossbar.



STEP 2: Fit rails to end frames and set length to fit worktops.




STEP 3: Align worktops to frame recommended spacing is 5 mm overhang on the ends.



STEP 4: Fix worktop to frame using 4 x 23mm screw per leg, 2 x 23mm screw per rail.

Plantation

Assembly Instructions - Desking Desk w/ Return






STEP 1: Follow straight desk instructions, then assemble 1x additional end leg.



STEP 2: Align main desk worktop and fit off.



STEP 3: a.) Fit end leg to return top at 5mm off the end of worktop.
b.) Fix the return bracket to the main worktop, making sure the join between the tops is tight.



STEP 4: Fit 2x joining plates to join.



Sydney 02 8188 2732
Melbourne 03 9111 0315
Brisbane 07 3733 1923
Adelaide 08 7111 0810
Perth 08 9468 2707

info@olgoffice.com

myolg.online | olgoffice.com | officedesigner.net | motionoffice.com